

Product Bulletin

Manufacturer

Atterotech

Product

InBox Series of CobraNet™ Wall Boxes
InBox X2, InBox M3, InBox R8



Product Brief Description

The Atterotech series of **InBox** products offer an ideal way to connect mics and line-level audio equipment to a CobraNet™ system. All of the InBox series wall boxes are designed to fit into a standard dual gang junction box and are PoE enabled, so all connectivity (both power and audio data) is provided by a single CAT-5 cable. Built-in DSP offers an equalizer, compressor, gain and delay, configurable on a per-channel basis.

The **InBox X2** is a two input, mic/line level wall box with switchable mic/line gain, switchable +12V phantom power, and clipping indicators for each channel.

The **InBox M3** is a multi-input wall box with a balanced XLR input, a pair of RCA inputs, and a stereo minijack input. All three inputs can be used simultaneously and all audio channels are available separately.

The **InBox R8** is an eight input, line level wall box with eight unbalanced RCA inputs which can be used as either eight mono inputs or four stereo inputs.

Features

Benefits

• CobraNet™ Ready	• Easy system integration
• Power and Audio on one cable	• Simplified interconnect (PoE Required)
• Built in DSP	• Conserve primary DSP resources
• Enclosure size: 3.60"W x 2.75"H x 1.88"D	• Fits Standard 2 gang wall boxes

Applications

- Hotel Ballrooms
- Conference Rooms
- Sports Facilities
- Convention Centers

Comparison Matrix

Features/Spec's	InBox X2	InBox M3	InBox R8
Inputs	2 x XLR	XLR, 2 x RCA, Stereo Mini	8 x RCA
List Price	\$669	\$669	\$669
Mic Input with Phantom Power	Yes	Yes	No
Black or White available	Yes	Yes	Yes